


AD00512-7/2

1/4*36(6.35Φ) - NO/CUT



MCX (J) FF(Front Feed)

SMA (J) BH HEX-8

L:14.5mm(5.3-1.2-8)

BO/GO, PI/GO

AD00512-7/2

Frequency	
Insertion Loss	
VSWR	
Impedance	■ 50Ω □ 75Ω
Temperature	-40℃ ~ 125℃

S11/S22/S21(SWR, SWR, dB)

■ _1,0GHz - 1,04, 1,04, 0,12
■ _2,0GHz - 1,06, 1,06, 0,07
■ _3,0GHz - 1,05, 1,06, 0,04
■ _4,0GHz - 1,06, 1,06, 0,00
■ _5,0GHz - 1,10, 1,10, 0,05
■ _6,0GHz - 1,19, 1,17, 0,06

■ _7,0GHz - 1,27, 1,30, 0,13
■ _8,0GHz - 1,30, 1,29, 0,09

► NETWORK ANALYZER

► Test cable

► Test Adaptor

■ E5071B (~8.5GHz)

□ ZVA50 (~50GHz)

TR1 : IN PORT VSWR(S11), TR2 : OUT PORT VSWR(S22), TR3: Insertion Loss (S21)

