

Operating Frequency range	MHz	2496-2690
Nominal Impedance	OHm	50
Return Loss (Min.)	dB	20
Insertion Loss (Max.)	dB	0.2
PIM Max. (2*43dBm)	dBc	-112
Insulation resistance (Min.)	mOHm	5000
Proofvoltage	V	1000
Leakage radiation (Min.)	dB	110
Power rating (Min.)	W	230

0.1	DATE		2017. 06. 30.		 RF & MICROWAVE TECHNOLOGY Tel : 82-32-347-8015 Fax : 82-32-347-8017		
	APPROVED BY	I.C.KIM					
1°	CHECKED BY			TITLE	4.1/9.5 DIN50 (P) MMCX50 (J) RA ADAPTER		
	DRAWN BY	S.Y.EUN					
	SCALE	UNIT		A3	DWG NO.	AD00592-7/1	
	1.5/1	mm			REVISION	1	SHEET

1. ④,⑤ PIN을 SOLDER 한다.
2. (1-2)번 BODY + ⑧번 TEFLON 을 조립한다.
3. (1-2) BODY + ③번 PIN을 조립한다.
4. SOLDER된 ④⑤PIN을 ③PIN에 나사 체결한다.
5. ②번 BODY + ⑦번 TEFLON을 조립한다.
6. (1-1)번 BODY + ②번 BODY를 억지끼움한다.
7. ⑬+⑨ COVER를 (1-1) BODY에 조립한다.
8. ⑭+⑫ CAP을 (1-2) BODY에 조립한다.
9. ⑧번 O링을 (1-2) BODY에 조립한다.

