



**SMA-PS+UHF-JB**  
**+141FJ(BLUE)**  
SMA PS 141TP  
BO/GO, PI/GO, CH/BR/NI  
UHF JB 141TP Screw  
BO/NI, PI/GO

### CF00079-7/1 152mm 8.5G

|                |               |
|----------------|---------------|
| Frequency      |               |
| Insertion Loss |               |
| VSWR           |               |
| Impedance      | ■ 50Ω □ 75Ω   |
| Temperature    | -40°C ~ 125°C |

### 152mm S11/S22/S21 (SWR, SWR, dB)

|           |                    |
|-----------|--------------------|
| ■ _1.0GHz | - 1.10, 1.10, 0.08 |
| ■ _2.0GHz | - 1.07, 1.06, 0.12 |
| ■ _3.0GHz | - 1.05, 1.05, 0.16 |
| ■ _4.0GHz | - 1.15, 1.15, 0.22 |
| ■ _5.0GHz | - 1.10, 1.10, 0.20 |
| ■ _6.0GHz | - 1.05, 1.04, 0.20 |
| ■ _7.0GHz | - 1.13, 1.10, 0.23 |
| -----     |                    |
| ■ _8.0GHz | - 1.19, 1.15, 0.22 |

#### ► NETWORK ANALYZER

#### ► Test cable

#### ► Test Adaptor

■ E5071B (~8.5GHz)

■ N Male to N Male

■ SMA (J) SMA (J) ST

□ ZVA50 (~50GHz)

10GHz Cable (CF00539-7/1)

AD00006-7/2

■ SMA (J) UHF (P) ST

TR1 : IN PORT VSWR(S11), TR2 : OUT PORT VSWR(S22), TR3: Insertion Loss (S21)

