

CF00090-7/2



BNC-PS+BNC-PS

+RG58 (BLACK)

BNC PS RG400

BO/NI, PI/GO, CAP/ZnDC/NI-KJ

CF00090-7/2 5M

Frequency	
Insertion Loss	
VSWR	
Impedance	■ 50Ω □ 75Ω
Temperature	-40°C ~ 125°C

5M - S11/S22/S21 (SWR, SWR, dB)

■_0.5GHz	- 1.13, 1.13, 1.78
■_1.0GHz	- 1.06, 1.10, 2.66
■_1.5GHz	- 1.15, 1.17, 3.43
■_2.0GHz	- 1.19, 1.19, 4.11
■_3.0GHz	- 1.17, 1.16, 5.38
■_4.0GHz	- 1.29, 1.36, 6.69
■_5.0GHz	- 1.61, 1.66, 8.30
■_6.0GHz	- 2.14, 2.24, 10.14

► NETWORK ANALYZER

► Test cable

► Test Adaptor

■ E5071B (~8.5GHz)

■ N Male to SMA Male

■ BNC (J) SMA (J) ST

□ ZVA50 (~50GHz)

10GHz Cable (CF00540-7/1)

TR1: IN PORT VSWR(S11), TR2: OUT PORT VSWR(S22), TR3: Insertion Loss (S21)

