

CF00118-7/2



BNC-JS+BNC-PS
+RG58 (BLACK)
BNC JS RG400
BO/NI, PI/GO
BNC PS RG400
BO/NI, PI/GO, CAP/ZnDC/NI

CF00118-7/2 5M

Frequency	
Insertion Loss	
VSWR	
Impedance	■ 50Ω □ 75Ω
Temperature	-40°C ~ 125°C

5M - S11/S22/S21 (SWR, SWR, dB)

■ _0.5GHz	- 1.10, 1.09, 1.76
■ _1.0GHz	- 1.13, 1.08, 2.66
■ _1.5GHz	- 1.14, 1.14, 3.42
■ _2.0GHz	- 1.20, 1.19, 4.12
■ _3.0GHz	- 1.10, 1.12, 5.30

■ _4.0GHz	- 1.22, 1.12, 6.59
■ _5.0GHz	- 1.59, 1.30, 8.15
■ _6.0GHz	- 1.87, 1.26, 9.75

► NETWORK ANALYZER

- E5071B (~8.5GHz)
- ZVA50 (~50GHz)

► Test cable

- N Male to SMA Male
- 10GHz Cable (CF00540-7/1)

► Test Adaptor

- BNC (P) SMA (J) ST
- BNC (J) SMA (J) ST

TR1 : IN PORT VSWR(S11), TR2 : OUT PORT VSWR(S22), TR3: Insertion Loss (S21)

